

This document provides additional assistance with wiring your Extron IP Link enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific Extron IP Link enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Switcher
Manufacturer: Intelix
Firmware Version: N/A
Model(s): DIGI-P123, DIGI-P122

Version History:

Driver Version	Date	IP Link Compiler	GC Version	Notes
3	10/22/2013	1.6.0	3.5.1	Added DIGI-P122 model.
2	9/27/2013	1.6.0	3.5.1	Fixed range for Mic Volume
1	9/5/2013	1.6.0	3.5.1	Initial version.

Driver Notes:

- Driver has been optimized for Volume.

IP Link® Device Interface Communication Sheet

Control Commands & States:

Auto Image	Execute		
Executive Mode	On	Off	
Freeze	On	Off	
Input	HDMI1	HDMI2	HDMI3
	HDMI4	VGA 1	VGA 2
	VGA 3	VGA 4	AV1
	AV2	YPbPr	S-Video
Line Mute	On	Off	
Line Volume (Discrete)	0 to 100 in steps of 1		
Line Volume (Step)	Up	Down	
Menu Navigation	Up	Down	Left
	Right	Menu	Enter
Mic Mute	On	Off	
Mic Volume (Discrete)	0 to 60 in steps of 1		
Mic Volume (Step)	Up	Down	
Mute All	On	Off	
Output Resolution	1360x768	1024x768	1280x720
	1280x800	1920x1080	

IP Link® Device Interface Communication Sheet

Status Available:


Connection Status	Connected	Disconnected	
Input	HDMI1	HDMI2	HDMI3
	HDMI4	VGA 1	VGA 2
	VGA 3	VGA 4	AV1
	AV2	YPbPr	S-Video
Line Volume (Discrete)	0 to 100 in steps of 1		
Mic Volume (Discrete)	0 to 60 in steps of 1		
Output Resolution	1360x768	1024x768	1280x720
	1280x800	1920x1080	

MLC60 Series Supported Commands:


Auto Image	Execute		
Executive Mode	On	Off	
Freeze	On	Off	
Input	HDMI1	HDMI2	HDMI3
	HDMI4	VGA 1	VGA 2
	VGA 3	VGA 4	AV1
	AV2	YPbPr	S-Video
Line Mute	On	Off	
Line Volume (Step)	Up	Down	
Menu Navigation	Up	Down	Left
	Right	Menu	Enter
Mic Mute	On	Off	
Mic Volume (Step)	Up	Down	
Mute All	On	Off	
Output Resolution	1360x768	1024x768	1280x720
	1280x800	1920x1080	

Cable and Adapter Requirements:

Female RS232 DB9 to 3pin captive screw

Notes for the Device:**Serial communication:****Port Type:** RS-232**Baud Rate:** 9600**Data Bits:** 8**Parity:** None**Stop Bits:** 1**Flow Control:** None**Pin Assignments Diagram:**

Signal	Pin	Main Cable	Pin	Signal
RxD	2	←	2	TxD
TxD	3	→	3	RxD
GND	5	→	5	GND



Note: Captive screw connector may also be used as a serial connection.

General Notes: